



*Electrical Distributors Co.*

KNOWLEDGE • SERVICE • INVENTORY  
ESTABLISHED 1948

Visit Us On The Web At: [www.electdist.com](http://www.electdist.com)

**SAN JOSE 95126**

1135 AUZERAIS STREET  
408-293-5818  
FAX: 408-287-1152

**GILROY 95020**

7120 ALEXANDER STREET  
408-847-2222  
FAX: 408-847-2324  
From Santa Cruz: 408-426-6464

**SALINAS 93901**

7 WORK CIRCLE  
831-422-4786  
FAX: 831-422-4846

**MONTEREY 93940**

2320 DEL MONTE AVE., #B  
831-373-4786  
FAX: 831-373-8430



# PHOTOTIMER - 5737TM

ON AT DUSK, OFF AT MIDNIGHT

Fits ordinary turn-lock photocontrol socket yet offers far greater energy savings



## SPECIFICATIONS

- Plugs into standard turn-lock receptacle
- All units meet or exceed ANSI C136.10

**Turns ON like a photocontrol,  
OFF like a time switch.**

- Microprocessor tracks the dusk and dawn times as they vary with the seasons and automatically determines midnight. No programming required.
- Off time during the night is user adjustable for specific needs such as extra energy savings or to customize for various longitudes
- Built in daylight savings time correction
- Automatically "relearns" and resets after power outage, thereby eliminating costly maintenance

# TORK

<b>Light Sensor:</b>	Silicon photosensor.
<b>DC Relay:</b>	Provides chatter free operation. Normally closed.
<b>Voltage Rating:</b>	105-305VAC.
<b>Load Rating:</b>	1,000 Watt Tungsten, 1800VA Ballast.
<b>Surge Protection:</b>	MOV (metal oxide varistor) 160 joules.
<b>Prongs:</b>	Solid brass for maximum corrosion resistance and electrical conductivity.
<b>Enclosure:</b>	UV stabilized ANSI color coded polypropylene dome.
<b>Window:</b>	UV stabilized, clear acrylic.
<b>Base:</b>	ABS.
<b>Gasket:</b>	Cross linked polyethylene.
<b>Turn ON/Turn OFF:</b>	Turn ON at dusk is 5.0 foot candle +/-0.5 OFF/ON ratio is 1.5:1 average.
<b>Time Delay ON/OFF:</b>	Instant ON, 3-5 seconds OFF.
<b>Fail ON:</b>	For safety reasons.
<b>Operating Temperature:</b>	-40°F to +158°F (-40°C to +70°C).